

SYN-S-R

Pairing to SYN-RC

Power on the SYN-RC receiver to be paired, then turn on the SYN-S-R remote (Indicator on remote should be on).

Click the Match Key on the SYN-RC receiver (do not hold down),
Then press the on/off button on the remote three times.

The LED products connected to the SYN-RC LED receiver will flash quickly indicating that the SYN-RC LED receiver is now paired with the remote.


Deleting a Pairing


Hold down the Match Key on the SYN-RC receiver for 10 seconds.
Connected LED lights will revert back to a default bright white.


Operating Distance


30m in clear air.



 : Turn on/off light.


 : Touch to change brightness.

 : Adjust brightness, short press 10 levels, long press 1-6s for continuous 256 levels adjustment.

 : Small night brightness (10%).

 : Turn off light after 30s, long press 2s will turn off light after 60s.

 : 25%, 50%, 75%, 100% brightness.

 : Short press recall the scene, long press 2s save current brightness into S1/2/3/4.
the LED indicator display green when save OK.

Disclaimer: While every care has been taken with the details of these products, Specialised LED Products Ltd accepts no responsibility for any inaccuracies. Specialised LED Products Ltd reserves the right to change the specifications without notice to continually ensure you receive a superior product.

innovative lighting solutions

www.sled.co.nz · sales@sled.co.nz · 09 420 3160

Specialised LED Products
Limited